VGA@BIOS utility is very easy to update VBIOS for your graphics card

Before update VBIOS, backup original VBIOS is needed. Please follow below step to backup and flash VBIOS for your graphics card.

1. VBIOS backup

Step1

Download VGA@BIOS utility and it.

🤰 VGA Tools @I	BIOS	Version 4.3	I
Description	VGA Tools @BIOS Support NVIDIA GeForce 7-series, 8-se Radeon 2-series, 3-series, 4-series ,5- OS:Windows XP 32bit,Windows XP 64 64bit,Windows 7 32bit,Windows 7 64b	ries, 9-series,200-serie series ,6-series models vit,Windows Vista 32bi it	es, 400 s. it,Windo
Download Here	Asia China America Europe Europe	(Russia) : FTP / Http	

Step2

Run VGA@BIOS and click "BACKUP VGA BIOS"



Step3

Select folder and click "save" to backup VBIOS

力性型陣						1 <u>1</u>
儲存於(I):	🔒 BIOS backuj	P	•	G	1 🖻 🖽 🕇	
C.	名稱	^			修改日期	
圣沙 最近的位置		没有	符合搜尋的項目	•		
夏面						
演員 媒體櫃						
電腦						
	•					,
通路	檔案名稱(N):	GV-N220UD-1GI.	F51		•	存檔(S)
8420	存檔類型(T):				•	取消

Step4

Click "OK" start to Save VBIOS

The screen may go	*BLANK* during EEPROM flash
	OK

VBIOS backup finish

Save VGA	NOS completed!!!	
	OK	

2. Flash VBIOS

Step1

Run VGA@BIOS and click "FLASH"



Step2

Select VBIOS file and Click "open"

● 開設茜檔		·····································			×
搜尋位置(I):	📕 vga_bios_n5	70o13i_f92	·• G	1 🗈 🛄 -	
Ca	名稱	× .		修改日期	3
▲ジ 最近的位置	N570O13I	.F92		2011/12/14 下午	02 I
夏面					
集體 櫃					
電腦					
G	•	m			•
網路	檔案名稱(N): 檔案類型(T):	N570013I.F92		 ■ 開設書 ■ 取 	[檔(O)] 消

Step3 Click "OK" to start flash VBIOS

The screen may go *BLANK* during EEPROM flash
OK

Step4

BIOS flash successes click "YES" reboot system to complete BIOS update.

	OK
_	
	restart your system to take new changes.
You must	
You must Do you wa	nt to restart now ?